

Clair Lighting

LED 120W Spot Wash Movinghead



User's Manual

1、Voltage: AC95V-245V/50Hz

2、Product power: 140W

3、Pattern parameters: 8pattern, 8colors

4、Bead parameters: 180W white light bead, 6 5050 8W RGBW bead

5、Control mode: International general-purpose DMX512, 15 channels

6、Working mode: DMX512, Master / slave , Autorun, Voice

7、Dimmer: 0~100% Ultra smooth dimming

8、Strobe: 25/s

Channels	Function	DMX Value	Description
1	X-axis motor	0-255	0~255 0-540° Rotate
2	Y-axis motor	0-255	0~255 0-180° Rotate
3	XY-axis motorspeed	0-255	0~255Speed from fast to slow
4	Total dimming	0-255	Linear dimming from dark to bright
5	Strobe	0-9	Nonfunctional
		10-255	Slow Fast
6	Color wheel	0-255	0-35 (switch one color every 5 intervals) , 35-127 (last color) , 127-255 (color from fast to slow)
			0-35 (switch one color every 5 patterns) , 35-127 (last pattern) , 127-255 (pattern from fast to slow)
7	Pattern wheel	0-255	
8	Prism	0-255	0-14(Nonfunctional), 15-255 (Prism from slow to fast)
9	Dyeing total dimming	0-255	Linear dimming from dark to bright
10	Dyed Strobe	0-9	Nonfunctional
		10-255	Slow Fast
11	Red	0-255	Linear dimming from dark to bright
12	Green	0-255	Linear dimming from dark to bright
13	Blue	0-255	Linear dimming from dark to bright
14	White	0-255	Linear dimming from dark to bright
15	Macro function control	0-50	Channel 1 to channel 14 effective
		51-150	Random self
		150-250	Walking sound control self
		251-255	3 seconds reset

Menu		
addr	A001-A512	Set 512 address
Chnd	15ch	display channel number
Shou (Operation mode)	d512	DMX 512 mode
	auto	auto mode
	sond	voice control mode
Sens	0-100	voice-controlled zero density setting
LED	oFF	Show often bright
	on	Show sleep
Disp	OFF	Show forward
	ON	Show reverse
rst	Yes/no	Manual reset