

## CLAIR LIGHTING HEX BEAM LIGHT

Channel	Function	DMX Value	Description
1	X motor	0-255	0-540 rotation
2	X motor speed	0-255	0-255 from fast to slow
3	Bee eye motor	0-127	0-180 degree rotation
		128-191	Non polar positive rotation
		192-255	Non polar reverse
4	Motor 1	0-255	0-180 degree rotation
5	Motor 2	0-255	0-180 degree rotation
6	Motor 3	0-255	0-180 degree rotation
7	Motor 4	0-255	0-180 degree rotation
8	Motor 5	0-255	0-180 degree rotation
9	Motor 6	0-255	0-180 degree rotation
10	Dimmer	0-255	Linear dimming from dark to light
11	Strobe	0-9	None
		10-55	Slow to fast
12	Bee eye red	0-255	Bee eye Red dimmer
13	Bee eye green	0-255	Bee eye Green dimmer
14	Bee eye blue	0-255	Bee eye Blue dimmer
15	Bee eye white	0-255	Bee eye White dimmer
16	Beam red	0-255	Beam Red dimmer
17	Beam green	0-255	Beam Green dimmer
18	Beam blue	0-255	Beam Blue dimmer
19	Beam white	0-255	Beam White dimmer
20	Red Laser	0-255	Red Laser dimmer
21	Green laser	0-255	Green Laser dimmer
22	Macro function control	0-50	Channel 1 to channel 21 active
		51-150	Auto run
		150-250	Voice
		251-255	Reset (3 seconds)

### Menu

Add	A001-A512	DMX 512 Setting
Chnd	22ch	Show number of channels
Shou (run mode)	d512	DMX512 mode
	auto	Auto run
	sond	voice
Sens	0-100	Voice control sensitivity
LED	oFF	Display constant brightness
	on	Display hibernation
Disp	OFF	Display forward
	ON	Display reverse
rst	Yes/no	Manual reset

### Specification

Voltage: AC95V-245 50HZ

Rated Power: 150W

Lamp: 10w X 10pcs CREE 4in1 , 50mW red green laser

Control mode: International DMX512

Channels: 22channels

Working mode: DMX512, Master-Slave , Auto, Sound control

Dimmer: 0-100% super smooth dimming

Stone: 20times per second

