

CLAIR LIGHTING DOUBLE SPINNER LIGHT

Channel	Function	DMX Value	Description
1	X motor	0-255	0-540 rotation
2	X motor speed	0-255	0-255 from fast to slow
3	Y motor 1	0-127	0-90 degree rotation
		128-191	Forward rotation from slow to fast
		192-255	Reverse rotation from fast to slow
4	Y motor 2	0-127	0-90 degree rotation
		128-191	Forward rotation from slow to fast
		192-255	Reverse rotation from fast to slow
5	Dimmer	0-255	Linear dimming from dark to light
6	Strobe	0-9	None
		10-55	Slow to fast
7	Red	0-255	Red dimmer
8	Green	0-255	Green dimmer
9	Blue	0-255	Blue dimmer
10	White	0-255	White dimmer
11	Green laser 1	0-255	Green laser dimmer
12	Green laser 2	0-255	Green laser dimmer
13	Macro function control	0-50	Channel 1 to channel 12 active
		51-150	Auto run
		150-250	Voice
		251-255	Reset (3 seconds)

Menu

Add	A001-A512	DMX 512 Setting
Chnd	Fast	Fast mode
	Slow	Slow mode
Shou (run mode)	d512	DMX512 mode
	aut1-aut4	Auto run 1 -auto run 4
	sou1-sou2	Voice 1-voice 2
Sens	0-100	Voice control sensitivity
LED	oFF	Display constant brightness
	on	Display hibernation
Disp	OFF	Display forward
	ON	Display reverse
rst	Yes/no	Manual reset

Specification

Voltage: AC95V-245 50HZ

Rated Power: 120W

Lamp: 10w X 8pcs CREE 4in1 , 100mW green laser x 2pcs

Control mode: International DMX512

Channels: 13channels

Working mode: DMX512, Master-Slave , Auto, Sound control

Dimmer: 0-100% super smooth dimming

Stone: 20times per second

