

CLAIR LIGHTING CONTROLLER

Specifications

DMX Output 2 x 512ch (1024Ch)

In Built Effect Generator

Programming- 3 easy access roller knobs for smooth transition in programming

Back up USB- backup system for saving shows and loading of R20 fixture personality

Up too 600 Scene Step

Scene and dimmer by slider

Playbacks Run up to 10 scenes/Chases simultaneously

Up to 30 Playbacks with 10 Playback faders

Mounting 19U Rack Mountable idea for on the road (mobile)

Dimensions (mm): 483 x 450 x 100 (LxWxH)

Library R20 type files

Programming is similar to Avolites platform

AVO1 1024 DMX CONTROLLER



AVO 2 SERIES 2 2048 DMX CONTROLLER



Specifications

Power: AC 90-240V / 50-60Hz

DMX Output: 2048

Channels Fixture: up to 200 fixtures

Channels for each fixtures: 40 primary+ 40 fine tune

Library: Works with R20 files

Scenes: 150 scene steps

Scenes to run simultaneously: 15 chases

Total Scene Steps: 600

Shape Generator: Shapes of Dimmer, Pan/Tilt, RGB,CMY, Color, Gobo, Iris and Focus
Shapes to run simultaneously: 8 built-in shapes

Dimension(mm): 600X460X110