

CLAIR LIGHTING CONTROLLER

24/48 Dimmer Console

Specifications

24-channel DMX-512 dimming console
4 pages with 12 scenes each yields 48 total
playback faders
(simultaneous playback)
96,000 programmable steps
2 programmable aux buttons
Adjustable chase and fade times
Re-assignable channels
LED lamp connector
Power: 12v dc 0.5A adaptor
Control Mode: Sound/ Auto/ Manual/ MIDI
Output: DMX XLR-3pin (male/female)
Dimension (mm): 483 X 264 X 90
Net Weight :4.5Kgs
ROHS CE Approved



Adjustable chase and fade time In built Mic
for easy sound mode control Password Lock
for presets Full on function with a touch on
one button All blackout function with a
touch of a button

DMX-384 CONTROLLER



Specification

Dimension(mm): 520 x 183 x 73
Weight: 3.0Kg
Operating range: DC9V-12V 500mA min
Data input: 3-pin XLR male socket
Data output: 3-pin XLR female socket
Protocols: DMX-512 USITT

Features

- DMX512/1990 Standard
- Controls 12 intelligent lights of up to 32channels
- 30banks, each with 8 scenes; 6 chase with up to 240 scenes
- Record up to 6chases with fade time and speeds
- 16 sliders for direct control of channels
- MIDI control over banks ,chases and blackout
- Built-in microphone for music mode
- Auto mode program controlled by fade time sliders
- DMX in/out : 3pin XLR
- LED gooseneck lamp